

# General product information page 1/2



## BATTERY LIFE

Candle:	up to 100 hours
Ambient:	up to 80 hours
Work:	up to 65 hours

## CHARGING

Charging in two ways possible:	with a power cable (USB-C to USB-A) and wirelessly.
Charging time to full power with USB cable:	up to 4 hours, depending on what adaptor is used.
Charging time to full power wirelessly:	up to 6 hours with 10W wireless charger.

Any Qi certified wireless charger is suitable to charge a Humble ONE light.

## BATTERY LEVEL

LED indicator lights on the base of the light will tell you the battery level.	
LED 1 flashing:	battery level < 5 % and in need of a charge.
1 LED on:	battery level is 6%–33%.
2 LED's on:	battery level is 34%–66%.
3 LED's on:	battery level is 67% – 100%.

To show you the battery level, the LED's will light up for 10 seconds after any brightness adjustment or after pressing the battery indicator button on the remote.

## BULB

The base is designed for use with replaceable low-voltage E27 bulbs.  
Note: The Humble lights will ONLY support low-voltage bulbs. The bulbs are separately available on our website: [www.humblelights.com](http://www.humblelights.com).

## MATERIALS

Base:	aluminium
Cover:	PBT or aluminium
Bulb:	glass
Seals:	silicon
Cable:	USB type-A to USB type-C (certified)

## TECHNICAL SPECS

Light source:	E27 low-voltage bulb
Power:	1W, 5V
Kelvin:	2200k
Dimmable:	yes, 3 levels
Lumen:	Candle 8 lm Ambient 16 lm Work 43 lm
Battery capacity:	4000 mAh
Charging cable:	USB-C to USB-A
Control:	Toggle switch on bottom of base

## CONTACT

Humble by Spacesplus B.V.  
Herengracht 189a  
1016 BE, Amsterdam  
The Netherlands

<b>e</b>	<a href="mailto:info@humblelights.com">info@humblelights.com</a>
<b>w</b>	<a href="http://humblelights.com">humblelights.com</a>
<b>i</b>	<a href="https://www.instagram.com/humble.lights">@humble.lights</a>

# General product information page 2/2

# humble one



Total weight: 310 grams



**Bulb**  
ST64 type glass bulb  
Swirl LED filament 2200 K  
Dimmable  
5V 1W

**Jacket**  
PBT or aluminium

**Base**  
Aluminium

**Battery level indicator LEDs**  
Display current level for 10 sec  
after any brightness adjustment

**USB-C charging port**  
Cable included

**Brightness toggle switch**  
Settings cycle:  
candle (low) > ambient (medium) > work (high) > OFF

- up to 100 hours of light
- dimmable 3 settings
- exchangeable bulb
- charge wirelessly
- control by remote (sold separately)